

PIEZO 6-11VDC/20MA/2.8KHZ/80DB PULSE

€ 5,95

Excl. BTW: € 4,92

Afbeeldingen



Beschrijving

Features

- Powerful Piezo Buzzer with mounting tabs
- Built-in drive circuit
- Wire connection terminals

Technical Specifications

Part No.	F_R	U_R	U_O	SPL_{min}	I_c	T_o
	[kHz]	[V DC]	[V DC]	[dB]	[mA]	[°C]
RMP28SW01P	2,8	1,5	1...3	70	20	-20...+70
RMP28SW01K	2,8	1,5	1...3	80	15	-20...+70
RMP28SW03P	2,8	3,0	2..5	75	15	-20...+70

RMP28SW03D	2,8	3,0	2..5	85	10	-20...+70
RMP28SW06P	2,8	6,0	4...9	80	15	-20...+70
RMP28SW06K	2,8	6,0	4...9	90	15	-20...+70
RMP28SW09P	2,8	9,0	6...11	80	20	-20...+70
RMP28SW09K	2,8	9,0	6...11	90	20	-20...+70
RMP28SW12P	2,8	12	8...15	85	25	-20...+70
RMP28SW12K	2,8	12	9...15	95	25	-20...+70
RMP28SW24P	2,8	24	15...28	85	25	-20...+70
RMP28SW24K	2,8	24	15...28	95	25	-20...+70

F_R = Resonant Frequency ($\pm 0,1$ =RMP-28SW_, $\pm 0,5$ =RMP-23SW, RMP-23SW-FL, $\pm 0,3$ =RMP-27SW), U_R = Rated Voltage, U_O = Operating Voltage Range, SPL_{min} = Min. Sound Output (@ U_N , $dB_{min}/30cm$ =RMP-28SW_, RMP-23SW, RMP-23SW-FL, $dB_{min}/10cm$ =RMP-27SW), I_C = Max. Current Consumption (@ U_N), T_O = Operating Temperature Range

Part No.	Tone	Puls Rate @ U_N [Pulse/Sec]
RMP28SW01P	Pulse	2..7
RMP28SW01K	Single	-
RMP28SW03P	Pulse	2..7
RMP28SW03K	Single	-
RMP28SW06P	Pulse	2..7
RMP28SW06K	Single	-
RMP28SW09P	Pulse	2..7
RMP28SW09K	Single	-
RMP28SW12P	Pulse	2..7
RMP28SW12K	Single	-
RMP28SW24P	Pulse	2..7
RMP28SW24K	Single	-

Productinformatie

Artikelnummer	RMP28SWO9P
Merk	EKULIT
Is on Sale	Nee

