

MOBIELE CB ZENDER 27MHZ 40KAN

€ 119,95

Excl. BTW: € 99,13

Afbeeldingen



Beschrijving

Als u op zoek bent naar een multifunctionele CB, dan is dit het model voor u. Klaar om u het beste van de M-serie te bieden, dankzij 6 programmeerbare toetsen, breed meerkleurig TFT-display en Dual Watch-functie om twee kanalen tegelijkertijd te monitoren. Automatische inschakeling, weergave van het kanaalnummer of kanaalnummer plus frequentie, maken het tot het perfecte hulpmiddel voor communicatieprofessionals.

Frequentiebereik: 26,965 - 27,405 MHz

Features

- Modulation: AM / FM
- Multi-bands: Yes
- Output power: 4 Watt / Duty cycle 10% @ 13.2V DC
- Channels: 40 AM / FM

- Display type: TFT display
- Display colors: White
- Noise blanker: Yes
- Squelch: DSS (Dynamic Squelch System)
- Emergency channel: Yes
- Keypad lock: Yes
- Scan function: Yes
- Memory channels: Yes
- External speaker socket: Yes
- S-meter: Yes

Electrical data

- Voltage: 13,8 Volt / 24 Volt /
- Operating temperature: -10° to +55° C
- Operating mode: F3E (FM) / A3E (AM)
- Frequency control: PLL synthesizer
- Frequency tolerance: 0.002%

Transmitter

- Audio frequency response: 300 Hz - 3 kHz
- Spurious transmissions: inferior to 4 nW (- 54 dBm)
- Emitted power in the adjacent channel: inferior a 20 µW

Receiver

- Frequency response: 300 Hz - 3 kHz
- Adjacent channel selectivity: 60 dB
- Maximum audio power: 3 Watt
- Internal speaker: 8 Ohm

Mechanical data

- Length: 160 mm
- Height: 38 mm
- Width: 120 mm
- Weight: 820 gram
- Antenna connector: UHF (PL) female (SO-239)
- Mike connector: RJ45 connector

Inside the box

- Transceiver: 1 pcs
- Microphone: 1 pcs
- Fixing screws: 1 set
- Mounting bracket: 1 pcs
- Power lead: 1 pcs
- User Manual: English, German, Spanish, Italian, French, Polish, Romania
- Microphone holder: 1 pcs

Artikelnummer	M30
Merk	MIDLAND
Is on Sale	Nee

