

CRT 2000H

€ 129,95

Excl. BTW: € 107,40

Afbeeldingen



Beschrijving

De CRT 2000H is een mobiele CB-radio geschikt voor 26,565-27,405 MHz. De radio is voorzien van een groot multifunctioneel display en een microfoon met Up/Down functie. Optioneel kan de radio via de computer worden geprogrammeerd met een programmeerkabel.

*Let op, de programmeerkabel is optioneel en niet inbegrepen!

Frequentiebereik: 26,965 - 27,405 MHz

Features

- Modulation: AM / FM
- Multi-bands: Yes
- Output power: 4 Watt

- Channels: 40 AM / FM
- Display type: LCD display
- Noise blanker: Yes
- Squelch: ASQ (Automatic Squelch System) / Manual squelch /
- Emergency channel: Yes
- Scan function: Yes
- External speaker socket: Yes
- S-meter: Yes
- RF gain: Yes
- TOT (time out timer): Yes
- Dual watch: Yes
- CTCSS: yes, 38 CTCSS
- DCS: Yes, 104 DCS
- Roger Beep: Yes
- Memory: Yes, 4 channels

Electrical data

- Voltage: 13,8 Volt
- Operating temperature: -20° to +55° C
- Operating mode: F3E (FM) / A3E (AM)
- Frequency control: PLL synthesizer

Transmitter

- Audio frequency response: 300 Hz - 3.0 kHz
- Frequency allowance: ± 5.0 ppm
- Drain: 2.0 A Max / Receive squelched 0.3 A / Vol max 0.8 A

Receiver

- AM sensitivity: 1.0 μ V for 10 dB
- FM sensitivity: 1.0 μ V for 10 dB
- Frequency response: 300 Hz - 3.0 kHz
- Adjacent channel selectivity: 60 dB
- Maximum audio power: 3 Watt
- Internal speaker: 8 Ohm, round
- IF frequencies: Double conversion 1st 10.695 MHz / 2nd 455 kHz
- Image rejection: 70 dB
- Squelch: Less than 1 μ V

Mechanical data

- Length: 124 mm
- Height: 39 mm
- Width: 163 mm
- Weight: 675 gram
- Antenna connector: UHF (PL) female (SO-239)
- Mike connector: RJ45 connector

Inside the box

- Transceiver: 1 pcs
- Microphone: 1 pcs
- Fixing screws: 1 set
- Mounting bracket: 1 pcs
- User Manual: English, French

Productinformatie

Artikelnummer	CRT2000H
Merk	CRT
Is on Sale	Nee

