

MIDLAND ALAN 48 PRO FOX HUNTING

€ 239,94

Excl. BTW: € 198,30

Afbeeldingen



Beschrijving

Het Midland Alan 48 Pro FOX-jachtpakket bevat een aangepaste Midland Alan 48 Pro die werkt met de K-PO S-27-signaalmeter.

De Midland Alan 48 Pro is het topmodel multiband, de CB-lijn uitdrukkelijk ontworpen voor reizen en routes in verschillende Europese landen. Wat betekent dit? Het betekent dat Alan 48 Pro een regelbaar vermogen – 1W/4W – heeft dat kan worden aangepast aan de frequenties en regelgeving van het land waarin het wordt gebruikt. Met een voedingsspanning van 12/24 V heeft de Alan 48 Pro geen verloopstukken nodig en is hij eenvoudig te installeren in het

dashboardcompartiment dankzij de DIN-beugel (optioneel). Alan 48 Pro is hightech en compleet in het omgaan met allerlei soorten geluiden: hij is uitgerust met de Digital Squelch, die het achtergrondgeluid elimineert, en de Noise Blanker, om omgevingsgeluiden te onderdrukken.

De K-PO S-27 is een externe signaalmetr (FOX-metr) en is ideaal voor 'FOX-jacht'. De K-PO S-27 heeft een sterke en robuuste metalen behuizing.

Frequentiebereik: 26,965 - 27,405 MHz

Features

- Modulation: AM / FM
- Multi-bands: Yes
- Output power: 1 - 4 Watt / Duty cycle 10% @ 13.8V DC
- Channels: 40 AM / FM
- Display type: LCD display
- Display colors: Blue
- Noise blanker: Yes
- Squelch: ASQ (Automatig Squelch Systeem) / DSS (Dynamic Squelch System) /
- Emergency channel: Yes
- Keypad lock: Yes
- Scan function: Yes
- Quick channel selection: Yes
- External speaker socket: Yes
- External S-meter socket: Yes
- External PA socket: Yes
- S-meter: Yes
- MIC gain: Yes
- RF gain: Yes
- Dual watch: Yes

Electrical data (Radio)

- Voltage: 13,8 Volt / 24 Volt
- Operating temperature: -10° to +55° C
- Operating mode: F3E (FM) / A3E (AM)
- Frequency control: PLL synthesizer
- Frequency tolerance: 0.002%

Transmitter

- Audio frequency response: 300 Hz - 3 kHz
- Modulation AM: from 85% to 95%
- Modulation FM: 1.8 kHz to ± 0.2 kHz
- Drain: 13.8 Volt: 1100 mA

Receiver

- AM sensitivity: 0.5 µV for 20 dB SINAD
- FM sensitivity: 0.5 µV for 20 dB SINAD
- Frequency response: 300 Hz - 3 kHz
- Adjacent channel selectivity: 65 dB
- Signal to noise ratio: 45 dB
- Maximum audio power: 2 Watt

- Internal speaker: 8 Ohm
- Receiving system: Dual conversion superheterodyne
- IF frequencies: Double conversion 1st 10.695 MHz / 2nd 455 kHz
- Audio distortion: Less than 8% @ 1 kHz
- Image rejection: 65 dB

Mechanical data (Radio)

- Length: 180 mm
- Height: 50 mm
- Width: 150 mm
- Weight: 1000 gram
- Mike connector: 6 pin connector

Electrical data (S-27)

- Impedance: 10K Ohm
- Voltage: 13.8 Volt, for display lightning only
- Sensitivity: 80 uA-'9'
- Illuminated display: Yes
- Power consumption: 50 mA

Mechanical data (S-27)

- Input connector: UHF (PL) female
- Output connector: UHF (PL) female
- Length: 80 mm
- Height: 80 mm
- Width: 170 mm
- Weight: 600 gram
- Connection: Ø 2.5 mm Jack

Inside the box

- Transceiver: 1 pcs
- Microphone: 1 pcs
- Fixing screws: 1 set
- Mounting bracket: 1 pcs
- Power lead: 1 pcs
- User Manual: English, German, Spanish, Italian, French, Polish, Romania
- Microphone holder: 1 pcs
- Meter: 1 pcs
- DC power cable: 1 pcs
-

Artikelnummer	ALAN48PROH
Merk	MIDLAND
Is on Sale	Nee



Productinformatie