

## GESCHAKELDE VOEDING SINGLE OUTPUT 636W 12V/53A

€ 189,00

Excl. BTW: € 156,20

### Afbeeldingen



### Beschrijving

#### Note

No load power consumption when Remote Control is off.  
You will find installation material in product group L9985.  
These power supplies are considered as a component that has to be installed in a final equipment.

## HRP-600

### Features

- Enclosed case, built-in fan, screw terminals
- Universal input
- Withstands 300V AC surge input for 5s
- Overload protection, current limiting, auto recovery
- Protections: short circuit/over load/over voltage
- Built-in active PFC function
- Long life 105°C electrolytic capacitors
- Built-in remote sense function
- DC OK signal

## HRPG-600

### Features

Same as HRP-600 but additional:

- Built-in remote On/Off control
- Low no load power consumption <0,75W
- Built-in auxiliary power, Stand by 5V/0,3A

### Technical Specifications

Input Voltage:	85...264V AC (47...63Hz)
	120...370V DC
Input Inrush Current, Max.:	70A
Leakage Current, Max.:	1,2mA
Over Load Protection:	105...135%
Withstand Voltage	
I/P-O/P:	3000V AC
I/P-FG:	2000V AC
O/P-FG:	500V AC

Operating Temperature:	-40...+70°C
Weight:	1580g

I/P = Input, O/P = Output, FG = Frame Ground

Part Nr.	$U_A$	$I_A$	$P_A$	$U_{adj}$	$DU_A$	$U_{RN}$	$h$
	[V]	[A]	[W]	[V]	[%]	[mV <sub>p-p</sub> ]	[%]
HRP-600-3.3	3,3	0...120	396	2,8...3,8	2	100	78,5
HRP-600-5	5	0...120	600	4,3...5,8	2	100	82
HRP-600-7.5	7,5	0...80	600	6,8...9	2	100	86
HRP-600-12	12	0...53	636	10,2...13,8	1	120	88
HRP-600-15	15	0...43	645	13,5...18	1	150	88
HRP-600-24	24	0...27	648	21,6...28,8	1	150	88
HRP-600-36	36	0...17,5	630	28,8...39,6	1	200	89
HRP-600-48	48	0...13	624	40,8...55,2	1	240	89
HRPG-600-3.3	3,3	0...120	396	2,8...3,8	2	100	78,5
HRPG-600-5	5	0...120	600	4,3...5,8	2	100	82
HRPG-600-7.5	7,5	0...80	600	6,8...9	2	100	86
HRPG-600-12	12	0...53	636	10,2...13,8	1	120	88
HRPG-600-15	15	0...43	645	13,5...18	1	150	88
HRPG-600-24	24	0...27	648	21,6...28,8	1	150	88
HRPG-600-36	36	0...17,5	630	28,8...39,6	1	200	89
HRPG-600-48	48	0...13	624	40,8...55,2	1	240	89

$U_A$  = Output Voltage,  $I_A$  = Output Current Range,  $P_A$  = Output Power,  $U_{adj}$  = Output Voltage Adjustment,  $DU_A$  = Output Voltage Tolerance,  $U_{RN}$  = Ripple & Noise,  $h$  = Efficiency

## Labelling

## Productinformatie

---

Artikelnummer	HRP60012
Merk	MEANWELL

