

PRESIDENT TAYLOR IV DM AM/FM

€ 209,95

Excl. BTW: € 173,51

Afbeeldingen



Beschrijving

Een moderne President-radio met veel functies verpakt in een klassieke uitstraling. Nu inclusief

President Digimike met NRC en functies zoals 7 verschillende displaykleuren, USB-oplaadpunt, klassieke analoge S-meter, menufuncties, PA-hoornaansluiting, 12/24 dubbele spanning en nog veel meer.

Frequentiebereik: 26,965 - 27,405 MHz

Features

- Modulation: AM / FM
- Multi-bands: Yes
- Output power: 4 Watt
- Channels: 40 AM / FM
- Display type: LCD display
- Display colors: Green / Orange / Purple / Blue / Cyaan / Yellow / Clear Blue
- VOX Function: Yes
- USB: Yes
- Noise blanker: Yes
- Squelch: ASQ (Automatig Squelch Systeem) / Manual squelch /
- Emergency channel: Yes
- Scan function: Yes
- External speaker socket: Yes
- External PA socket: Yes
- S-meter: Yes
- Digimike with NRC: Yes
- Display: Multi-functions / Frequencies
- Talkback function: Yes
- Key beep: Yes
- Roger beep: Yes
- Microphone type: Electret / Dynamic
- F / Menu function key: Yes
- SWR (Power Reading / SWR): Yes
- Filter HI-CUT: Yes
- Dimmer: Yes
- External VOX jack: Yes

Electrical data

- Voltage: 13,8 Volt / 24 Volt /

Transmitter

- Audio frequency response: 300 Hz - 3 kHz
- Microphone sensitivity: 1,0 mV
- Frequency allowance: +/- 300 Hz
- Transmission interference: inferior to 4 nW (- 54 dBm)
- Emitted power in the adjacent channel: inferior to 20 µW
- Drain: 1.7 A (with modulation)
- Modulated signal distortion: 1,8 %

Receiver

- AM sensitivity: 0.5 μ V - 113 dBm
- FM sensitivity: 0.5 μ V - 113 dBm
- Frequency response: 300 Hz - 3 kHz
- Adjacent channel selectivity: 60 dB
- Maximum audio power: 5 Watt
- Squelch sensitivity: minimum 0.2 μ V - 120 dBm / maximum 1 mV - 47 dBm
- Frequency image rejection rate: 60 dB
- Intermediate frequency rejection rate: 70 dB
- Drain: 500 mA nominal / 800 mA maximum

Mechanical data

- Length: 150 mm
- Height: 45 mm
- Width: 165 mm
- Weight: 750 gram
- Antenna connector: UHF (PL) female (SO-239)
- Microphone connector: 6 pin

Inside the box

- Transceiver: 1 pcs
- Fixing screws: 1 set
- Mounting bracket: 1 pcs
- Power lead: 1 pcs
- User Manual: English, Spanish, French, Polish
- Digimike NRC: 1 pcs

Productinformatie

Artikelnummer	TAYLORIV
Merk	PRESIDENT
Is on Sale	Nee

