


PRESIDENT RANDY III 27MHZ PORTOFOON

€ 219,95

Excl. BTW: € 181,78

Afbeeldingen



Beschrijving

De President Randy III is de opvolger van de Randy II en is zowel qua design als intern verbeterd. De Randy III heeft de meest essentiële functies die u van een CB-handradio kunt verwachten.

Frequentiebereik: 26,965 - 27,405 MHz

Features

- Modulation: AM / FM
- Multi-bands: Yes
- Output power: 4 Watt
- Channels: 40 AM / FM
- Front speaker: Yes

- Display type: LCD display
- Display colors: Green / Orange / Purple / Blue / Cyan / Yellow / Clear Blue
- VOX Function: Yes
- Noise blanker: Yes
- Squelch: ASQ (Automatic Squelch System) / Manual squelch /
- Emergency channel: Yes
- Keypad lock: Yes
- Hi/Lo power: Yes
- Scan function: Yes
- Memory channels: Yes
- External speaker socket: Yes
- S-meter: Yes
- Dual watch: Yes
- Car socket connector: Yes
- Battery capacity: Li-ion 1800 mAh
- External VOX microphone socket: Yes, Ø 2.5 mm
- Drain: ECO mode
- CTCSS: Yes, 38 tones
- DCS: Yes, 104 codes

Transmitter

- Audio frequency response: 300 Hz - 3 kHz
- Microphone sensitivity: 7 mV
- Frequency allowance: ± 200 Hz
- Transmission interference: inferior to 4 nW (-54 dBm)
- Emitted power in the adjacent channel: inferior a 20 μ W
- Modulated signal distortion: 1.8 %
- Drain: <1.8 A

Receiver

- AM sensitivity: 0,5 μ V - 113 dBm
- FM sensitivity: 0,35 μ V - 116 dBm
- Frequency response: 300 Hz - 3 kHz
- Adjacent channel selectivity: 60 dB
- Maximum audio power: 1 Watt
- Squelch sensitivity: min. 0.2 μ V - 120 dBm / max. 1 mV - 47 dBm
- Frequency image rejection rate: 60 dB
- Intermediate image rejection rate: 70 dB
- Drain: Mode ECO

Mechanical data

- Length: 37 mm
- Height: 152 mm
- Width: 67 mm
- Weight: 305 gram
- Antenna connector: TNC
- Accessory connector: 2 pin Standard Icom (S)

Artikelnummer	RANDYIII
Merk	PRESIDENT
Is on Sale	Nee

