

## LIVE MIXER GIG-83CFX 8 KANAALS

€ 249,01

Excl. BTW: € 205,79

### Afbeeldingen



### Beschrijving

The GIG-83 CFX Mixing Console is packed with features that cannot be found in other consoles of its size: 4 mono (provided with ultra low noise microphone pre amplifiers and Phantom Power at +48 Volt ) and 3 stereo input channels. Each of them are provided with a 3-band equalizer for HI, MID and LOW controls, as well as 1 auxiliary control, built-in 24-bit DSP effect with 100 presets, highly accurate 8-segment bar graph meters and 2-track inputs assignable to main mix, control room/phones or group outputs.

Specifications

Mono Channels

Mic Input: XLR balanced  
Line input: 1/4- TRS balanced  
Freq response: 10Hz ~ 55kHz, +/- 3dB  
Distortion (THD=N): <0,03% @ 0dB, 22Hz ~ 22kHz  
Gain range: 50dB  
Input sensitivity: -35dBu ~ +15dBu  
LOW Cut: 75Hz  
SNR <-100dBr  
Phantom Power: +48V switchable

#### Stereo Channels

Mic Input: XLR balanced  
Line input: 1/4- TRS/RCA unbalanced  
Freq response: 10Hz ~ 55kHz, +/- 3dB  
Distortion (THD=N): <0,03% @ 0dB, 22Hz ~ 22kHz  
Gain range: 50dB  
Input sensitivity: -20dBu ~ +20dBu  
LOW Cut: 75Hz  
SNR <-100dBr  
Phantom Power: +48V switchable

#### Channels EQ

High: +/- 15dB @ 12kHz  
Mid: +/- 15dB @ 2,5kHz  
Low: +/- 15dB @ 80Hz

#### Impedances

Microphone input: 1,8K Ohm  
Other inputs: >10K Ohm  
Tape output: 1K Ohm  
All other outputs: 120 Ohm

Power supply: AC 100- 240V 50Hz/60Hz

Power consumption: 40 Watt

Measurements: 343 x 254 x 63mm

Weight: 2,48 Kg

## Productinformatie

---

|               |           |
|---------------|-----------|
| Artikelnummer | D2282     |
| Merk          | DAP AUDIO |
| Is on Sale    | Nee       |

