

## INSTALL MIXER IMIX-7.2 6U 7 KANAALS 2 ZONES

€ 999,00

Excl. BTW: € 825,62

### Afbeeldingen



### Beschrijving

The IMIX-7.2USB is a unique installation mixer. It's a 6U, 7 Channel, 2 Zone mixer with 2 built-in USB audio interfaces especially designed to fulfill all audio needs of a pub, school, small disco without scarifying on the ease of use. It is the world first installation mixer that shows the active channel source on a display. This will help users to select the desired source for the desired area. Each in- and output has own individual VU meters which gives you total level information in one view. The channel gain must be set at the back to prevent wrong use by non-technical users. The displays are pre-programmed with 16 different source names which can be set at the backside by an installer. It has 2 microphone inputs with an easy-to-use reverb effect and talk-over function. At the front it has direct inputs for a microphone, a line input and a dedicated phone/mp3 input. With a pair of headphones you can monitor all out- and inputs.

### Specifications

Input channels: 2 x Microphone, combo XLR/Jack

8 x Line, RCA  
2 x audio interface, USB-B chassis  
1 x Phone, 3,5mm jack  
Output channels: 2 x Master Balanced, XLR/RCA  
1 x Record, RCA  
1 x Monitor, RCA  
1 x Headphones, 6.3mm Jack  
Display presets: CD 1, CD 2, TUNER, DVD, TV, BEAMER, PC1,  
PC2, DJ, AREA 2, AUX 1, AUX 2  
USB interfaces: 48Khz, 16bit plug & play for windows and MAC  
Channel EQ: 80Hz, 1KHz, 12KHz, -12dB / +12dB  
Mic EQ: 120Hz, 800Hz, 5KHz, -12dB / +12dB  
Frequency response: 20Hz – 20KHz  
T.H.D.: <0.05%  
Dimensions: 481 x 266 x 135 mm (LxHxD)  
Powersupply: 110-230V AC, 50/60Hz  
Powerconsumption: 32Watt  
Weight: 6,4 Kg

## Productinformatie

---

Artikelnummer	D2353
Merk	DAP AUDIO

