

VERSTERKER 100V 120W MET FM TUNER USB EN 2 ZONES**€ 625,00**

Excl. BTW: € 516,53

Afbeeldingen**Beschrijving**

The DAP ZA-9120TU is a 120Watt, 100V mixer amplifier with 7 selectable sources, 3 microphone inputs and 2 zones. All microphone inputs are equipped with phantom power and can also be selected as line input. An integrated speech filter can be applied to improve the audibility. It has 3 dedicated line inputs on the backside and a special easy access line/phone front input to connect mp3 players or mobile devices. It has a built-in USB audio player and tuner with a large LCD display which shows the active source, tuner information and ID3 tags. The built-in FM tuner can store 10 presets. The amplifier also has enhanced features such as, priority, chime with adjustable level, emergency input, ducking level control, loop through connection and an output which can be set as line output, music only or microphone only. Each zone also has its own line outputs to connect extra amplifiers and extend the PA system. The ZA-9120TU is the ideal easy to use one-in-all solution for medium size PA systems.

These amplifiers are designed for PA systems with applications such as announcement, intercommunication, background music and broadcasting in convention-halls, shopping centers, dining rooms, auditoriums and recreation areas. These desk top amplifiers have an integrated protective circuit to withstand overload or short-circuits of output. This results in very high reliability and easy installations without extra audio processors. It is a complete range from simple amplifiers till matrix amplifiers with built-in tuner and media player.

Specifications

Outputs

Power: 120W

Zones: 2

100V & 80hm: Terminals

Line output: XLR

Loop through: RCA

Headphones: 6,3mm Jack

Inputs:

3x Mic/Line: XLR/Jack combi & Terminals

3x Line: RCA

Front input: 3,5mm Jack

Media player

Source: 2x USB type A, front/back

Supported files: MP3, Wav

Format: FAT32 up to 32Gb

Playback: Program, Repeat, Continuous

Tuner

FM band: 87,5 – 108 MHz

Presets: 10

Antenna: 75Ohm

Features

Speech filter: -3dB, 300Hz 6db/oct

Phantom power: 18V

Tone Control: Bass 100 Hz, treble 12 KHz, +/-12dB

Chime: adjustable volume

Ducking: adjustable suppression

PTT: Mic input 1

VOX: Mic input 2

Telephone input: Override all, terminal

General

Power supply: 230V AC

Back-up power supply: DC 24V

Power consumption: 250W

Power connection: IEC

Dimensions: 483x328x88mm (WxDxH)

Weight: 9 Kg

Productinformatie

Artikelnummer	ZA9120TU
Merk	DAP AUDIO

