

## EMI NETFILTER 1 FASE 2 TRAPS 250V 16A MET 6,3MM FASTON AANSLUITING

€ 91,44

Excl. BTW: € 75,57

### Afbeeldingen



### Beschrijving

#### Features

- Single phase filters, two-stage, built in a metal housing
- Faston plug terminal 6,3x0,8mm
- Compact design
- Universal application
- 

#### Technical Specifications

Continuous Operating Voltage, Max.:

250V AC, 50/60Hz; 250V DC

Dielectric Strength, 2s	
Line To Ground:	2kV AC
Line To Ground B-Types:	2,5kV AC
Line To Neutral:	1,1kV DC
Temperature Range:	-25...+100°C

Part Nr.	$I_R$	L	L1	$C_x$	$C_y$	$I_L$
	[A]	[mH]	[ $\mu$ H]	[ $\mu$ F]	[nF]	[mA]
FN2080-1F	1	22	490	0,33	4,7	0,66
FN2080-3F	3	9,8	160	0,47	4,7	0,66
FN2080-6F	6	7,8	110	1	4,7	0,66
FN2080-10F	10	4,5	60	1	4,7	0,66
FN2080-12F	12	3,25	50	1	4,7	0,66
FN2080-16F	16	2,8	43	1	4,7	0,66

$I_R$  = Rated Current, at 40°C, L = Inductance,  $I_L$  = Leakage Current, Max. at 250V AC, 50Hz

## Approvals



## Productinformatie

Artikelnummer	FN2080-16F
Merk	SCHAFFNER

