

**PORTOFOON 446MHZ 0,5W 16KAN 6 STUKS MET ACCU EN 6 VOUDIGE
LADER**

€ 1.119,00

Excl. BTW: € 924,79

Afbeeldingen



Beschrijving

The Wouxun KG-D26 Energy package is a set with 6 radios and an 6 way charger.

The Wouxun KG-D26 dPMR is fully compatible, analog and digital, with the Kenwood TK-3401D, TK-3601D and TK-3701D series. The hidden display is integrated in the strong radio body, which prevent it from damaging. It will clearly show you the: Channel number, Analogue / digital mode, Current zone, High / low power, Narrow / wide bandwidth, Battery status, Signal status, VOX indicator, DCS/CTCSS indicator and Time slot 1 / 2 indicator.

Features

- Number of channels: 16
- Number of zones: 99 programmable (3 zones preprogrammed)
- Output power: 0.5 / 6 Watt
- Channel spacing analogue: 12.5 kHz
- Channel spacing digital: 6.25 kHz
- Call alert: Yes
- Key lock: Yes
- Programmable function keys: Yes
- PC programming: Yes
- Display: Yes
- Display colors: Green
- High/low power: Yes
- Battery capacity: Li-ion 2000 mAh
- Accessory connector: 2-pin Kenwood connector (K)
- Voice guide: English and Chinese
- VOX: Yes, activation by software
- Scan: Yes, activation by software
- Flashlight: Yes
- RX group list: 32 groups, 8 members per group
- Scanning list: 16 groups, 16 channels per group

Mechanical data (radio)

- **Length:** 53 mm
- **Height:** 245 mm
- **Width:** 33 mm
- **Weight:** 245 gram
- **Antenna connector:** SMA male
- **Operating voltage:** 7.5V DC +/- 20%
- **Battery life:** Battery save off: 24 hours, battery save on: 30 hours (5% transmit, 5% receive, 90% standby)

Features (6 way charger)

- **Suitable for:** Wouxun KG-D26 / Wouxun KG-D901 / Wouxun KG-UV9D / Wouxun KG-UV9D Plus / Wouxun KG-UV9K /
- **Input voltage:** 230 Volt
- **Battery charging function:** Yes
- **Number of radios:** 6

Productinformatie

| | |
|---------------|-----------|
| Artikelnummer | KG-D26/E6 |
| Merk | WOUXUN |
| Is on Sale | Nee |

