

VOORVERSTERKERBUIS 9P NOVAL DUBBEL TRIODE

€ 28,75

Excl. BTW: € 23,76

Afbeeldingen



Beschrijving

R. F. DOUBLE TRIODE

Base: NOVAL

Uf = 6,3/12,6 V

If = ca.300/150 mA

Typical

characteristic:

Ua = 250 V

$U_g = -8,5 \text{ V}$
 $I_a = 10,5 \text{ mA}$
 $S = 2,2 \text{ mA/V}$
 $R_i = 7,7 \text{ k}\Omega$
 $i = 17$
 Limiting values:
 $U_a = 300 \text{ V}$
 $W_a = 2,75 \text{ W}$
 $I_k = 20 \text{ mA}$
 $U_g = -50 \text{ V}$
 $R_g = 1 \text{ M}\Omega$
 $U_{k/f} = 180 \text{ V}$
 $R_{k/f} = 150 \text{ k}\Omega$
 Capacitances:
 system I. system II.
 $c_{g/k} = 1,9 \text{ pF}$
 $c_a = 1,8 \text{ pF}$
 $c_{g/a} = 1,63 \text{ pF}$
 As phase inverter:
 $U_b = 250 \text{ V}$
 $I_a = 0,7 \text{ mA}$
 $I_{a'} = 0,68 \text{ mA}$
 $U_o/U_{g1} = 11$
 $U_o = 15 \text{ V RMS}$
 $\text{d}t_{\text{tot}} = 11 \%$

Productinformatie

Artikelnummer	ECC82
Merk	JJ ELECTRONIC
Is on Sale	Nee

